



GE
Lighting

78710 - CSR24000/DE
CSR24000/DE



GENERAL CHARACTERISTICS

| | |
|---------------------|--|
| Lamp Type | High Intensity Discharge - Quartz Metal Halide |
| Bulb | T28 |
| Base | 30x70 Cyl 165mm |
| Rated Life (NOM) | 400.0 h |
| Primary Application | Stage & Studio |

PHOTOMETRIC CHARACTERISTICS

| | |
|---------------------------------------|-----------|
| Initial Lumens (NOM) | 2300000.0 |
| Nominal Initial Lumens per Watt (NOM) | 95.83334 |
| Color Temperature (NOM) | 6000.0 K |
| Color Rendering Index (CRI) (NOM) | 90.0 |

ELECTRICAL CHARACTERISTICS

| | |
|---------------|---------|
| Wattage (NOM) | 24000.0 |
| Voltage (NOM) | 270.0 |
| Burn Position | H15 |

DIMENSIONS

| | |
|------------------------------------|---------------------|
| Maximum Overall Length (MOL) (NOM) | 19.680 in(499.9 mm) |
| Bulb Diameter (DIA) (NOM) | 3.500 in(88.9 mm) |
| Light Center Length (LCL) (NOM) | 3.0E-37 |

PRODUCT INFORMATION

| | |
|----------------------------------|----------------|
| Product Code | 78710 |
| Description | CSR24000/DE |
| ANSI Code | GE2005-7888 |
| Standard Package | 00-Case |
| Standard Package GTIN | 10043168787106 |
| Standard Package Quantity | 1 |
| Sales Unit | Unit |
| No Of Items Per Sales Unit | 1 |
| No Of Items Per Standard Package | 1 |
| UPC | 043168787109 |

CAUTIONS & WARNINGS

Caution

- Cut hazard--possible jagged glass
 - Wear gloves when handling
- Risk of Burn
 - Allow lamp to cool before handling.
- Lamp may shatter and cause injury if broken
 - Dispose of lamp in a closed container.
- Risk of Burn
 - Do not turn on lamp until fully installed.
- Lamp may shatter and cause injury if broken
 - Do not use excessive force when installing lamp.
- Lamp may shatter and cause injury if broken
 - Do not use lamp if outer glass is scratched or broken.
- Cut hazard--possible jagged glass
 - Wear gloves when handling
- Risk of Burn
 - Allow lamp to cool before handling
 - Do not turn on lamp until fully installed
- Lamp may shatter and cause injury if broken
 - Dispose of lamp in a closed container
 - Do not use excessive force when installing lamp
 - Do not use lamp if outer glass is scratched or broken

Warning

- Lamp emits UV radiation which may cause eye/skin injury. RG-3
 - Avoid exposure of eyes and skin to unshielded lamp.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not exceed rated voltage.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not store flammable materials near/below lamp.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not touch glass with bare hands.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not turn on lamp until fully installed.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not use beyond rated life.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not use lamp if outer glass is scratched or broken.
- Risk of Electric Shock
 - Do not use where directly exposed to water or outdoors without an enclosed fixture.
- Risk of Fire
 - Keep combustible materials away from lamp.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Operate lamp only in specified position.
- Risk of Electric Shock
 - Turn power off before inspection, installation or removal.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Use in enclosed fixture rated for this product.
- Risk of Fire
 - Use in enclosed fixture rated for this product.
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Use only properly rated ballast.
- Lamp emits UV radiation which may cause eye/skin injury. RG-3
 - Avoid exposure of eyes and skin to unshielded lamp
- Unexpected lamp rupture may cause injury, fire, or property damage
 - Do not turn on lamp until fully installed
 - Do not use lamp if outer glass is scratched or broken
- Risk of Fire
 - Keep combustible materials away from lamp
 - Use in enclosed fixture rated for this product
- Risk of Electric Shock
 - Do not use where directly exposed to water or outdoors without an enclosed fixture
 - Turn power off before inspection, installation or removal

Distributor:


Techni-Lux

Phone: 407-857-8770

Fax: 407-857-8771

www.techni-lux.com