

Product Type	=D*) 'L@F 'D`i [
Product Model	G7 K A) !6
Customer Name	

Manufactura	Prepared	Checked	Approved
Manufacturer			

0	Received	Checked	Confirmed
Customer			



Phone: 407-857-8770 Fax: 407-857-8771 Email: sales@techni-lux.com www.techni-lux.com





Product Type	IP65 XLR Plug	
Product Model	SCWM5-B	

Product Features

- > 5-core waterproof XLR male cable connector with black plated housing and gold plated contacts
- Waterproof rating IP65
- > The metal housing uses internal thread design to ensure that it can withstand gravity under any site conditions
- Cable O.D.: 5-8mm
- ➤ No ring design, more compact
- The boot is equipped with a polyurethane sealing sleeve to prevent the cable from being affected by bending pressure to the greatest extent



Product Parameters

Item	Specification
Connection Type	XLR
Gender	Male

Electrical Parameters

Item	Specification
Capacitance between contacts	≤ 7 pF
Contact resistance	≤ 3 mΩ
Dielectric strength	1.5 kV DC
Insulation resistance	> 10 GΩ (initial)
Rated current per contact	7.5 A
Rated voltage	< 50 V



Mechanical Parameters

Item	Specification
Cable O.D.	5~8 mm
Insertion force	≤ 20 N
Withdrawal force	≤ 20 N
Service life	> 1000 mating cycles
Cable size	Max.1.0 mm ² Max.18 AWG
Locking device	Latch lock



Material and Environmental Parameters

Item	Specification
Boot	PA
Contacts	Cu alloy
Contact plating	Au
Insert	PA
Housing	Zinc alloy
Housing plating	Black plating
Strain relief	РОМ
Flame-retardant grade	UL 94 HB
Protection class	IP65
Temperature range	-30°C ~ +80°C

Standards and Certifications

Standards	IEC 61076-2-103
Solderability	Complies with IEC 68-2-20



Packaging Method

1 pc per bag (include 1 pc each of inner core, housing, waterproof cable clamp, boot) 80 pcs per inner carton, 5 inner cartons per master carton (400 pcs per master carton)

Accessory

✓ No accessories

Screws and Nuts

- ☐ Back fastener plate
- □ Other



Assembly Instructions

(1) Put the cable through the boot and waterproof cable clamp	
(2) Strip the cable in the size as shown	4.00
(3) Insert the conductor of the cable into the terminal of the inner core and solder	
(4) Snap the clamp into the inner core assembly bayonet	



(5) Push the inner core component and clamp into the housing. The two protruding ribs of the inner core component should correspond to the two grooves inside the housing.

(6) After the assembly of the cable clamp, inner core and housing, tighten the boot in a clockwise direction.