



Product Data Sheet

Product Type IP65RJ45 Plug

Product Model SE8MH-02-B-LOD

Customer Name _____

Manufacturer	Prepared	Checked	Approved

Customer	Received	Checked	Confirmed

Distributor:



Phone: 407-857-8770
Fax: 407-857-8771
Email: sales@techni-lux.com
www.techni-lux.com



Product Data Sheet

Product Type	IP65 RJ45 Plug	
Product Model	SE8MH-02-B-LOD	
Product Features		
<ul style="list-style-type: none">➤ RJ45 cable carrier connector, stainless steel housing➤ Ideal for any harsh and demanding outdoor environment with waterproof rating IP65➤ Works with most RJ45 chassis connectors in the market➤ Cable connector carrier does not include RJ45 plug➤ Cable O.D. 7.5-9 mm➤ Durable die-cast shell and unique cable clamp➤ Sleek design protects Ethernet connections in most commercial type applications and components of standard RJ45 plugs		



Product Data Sheet

Product Parameters

Item	Specification
Connection Type	RJ45
Gender	Male

Mechanical Parameters

Item	Specification
Cable O.D.	7.5-9mm
Insertion force	≤ 20 N
Withdrawal force	≤ 20 N
Service life	> 1000 mating cycles
Locking device	Latch lock


Material and Environmental Parameters

Item	Specification
Boot	PA
Housing	Stainless steel
Housing plating	Black plating
Protection degree	IP65
Temperature range	-30°C ~ +80°C



Product Data Sheet

Product Drawing



Unit: mm

Packaging Method

1pc per bag (including 1pc each of housing, cable clamp and boot)
80pcs per inner carton, 5 inner cartons per master carton (400 pcs per master carton)

Accessory


- | | |
|--|--|
| ☒ No accessories | ☐ Back fastener plate |
| ☐ Screws and Nuts | ☐ Other |




Product Data Sheet

Assembly Instructions

- (1) Thread the cable through the boot and the waterproof cable clamp.




- (2) Assemble the cable with RJ45




Product Data Sheet

Assembly Instructions

- (3) Put the RJ45 into the cable clamp and fasten the cable clip




- ① The A1 and B1 sides of the RJ45 correspond to the A2 and B2 sides of the cable clip respectively.



- ② RJ45 sheeting presses into cable clip block


- ③ Close the cable clamp



Product Data Sheet

Assembly Instructions

- (4) Push the assembled cable clamp and RJ45 into the housing



- (5) After assembly of the cable clamp, RJ45 and housing, tighten the boot in a clockwise direction

