

mSculpt 20 LED Profile v1.0


Dip Switch Settings
DMX Channel Layout



TH-SCLPM20
For v1.0 with DIP Switches Only


DIP SWITCH SETTINGS

TH-SCLPM20QW RGBW or QA RGBA models



- Red
- Green
- Blue
- Yellow
- Magenta
- Cyan
- White
- Red and Green
- Red and Blue
- Red and White
- Green and Blue
- Green and White
- Blue and White
- Red, Green and Blue
- Red, Green and White
- Green, Blue and White

TH-SCLPM20WW Warm White or CW Cool White models



- Open
- Strobe

DMX CHANNEL LAYOUTS

TH-SCLPM20QW RGBW or QA RGBA models
8 Channel DMX control

CHANNEL	VALUES	EFFECT
1	000-255	Dimmer intensity 0-100%
2	000	Shutter open
	001-127	Strobe effect with increasing speed
	128-159	Strobe effect with increasing speed
	160-191	Pulse effect with increasing speed
	192-255	Random strobe effect with increasing speed
3	000-255	Rainbow effect
4	000-255	Rainbow speed
5	000-255	Red, intensity 0-100%
6	000-255	Green, intensity 0-100%
7	000-255	Blue, intensity 0-100%
8	000-255	White, intensity 0-100%

TH-SCLPM20WW Warm White or CW Cool White models
2 Channel DMX control

CHANNEL	VALUES	EFFECT
1	000-255	Dimmer intensity 0-100%
2	000	Shutter open
	001-127	Strobe effect with increasing speed
	128-159	Strobe effect with increasing speed
	160-191	Pulse effect with increasing speed
	192-255	Random strobe effect with increasing speed